

POMPE CON VARIATORE O INVERTER

PUMPS WITH MECHANICAL SPEED VARIATOR OR FREQUENCY CONVERTER

10



POMPE CON VARIATORE (VA)
PUMPS WITH MECH. SPEED VARIATOR (VA)

POMPE CON INVERTER (INV)
PUMPS WITH FREQUENCY CONVERTER (INV)

| Tipo Type | Alimentazione/Feeding | | Giri/min Rpm | H (m) = Prevalenza / Head - Q (l/h) = Portata / Capacity | | | | | | | | | | | | | |
|---------------------------|-------------------------|---------------------|-----------------|--|---------|-------|-------|-------|-------|-------|------|------|------|----|----|---|--|
| | Tipo/Type * | HP | | kW | 0 | 4 | 8 | 12 | 16 | 18 | 20 | 24 | 27 | 32 | 40 | H | |
| VA MINOR 40 | TF 230-400V 50 Hz | 2 | 1,5 | min 175 | 1320 | 0 | | | | | | | | | | | |
| | | | | 350 | 2750 | 2500 | 2100 | 1600 | 800 | 0 | | | | | | | |
| | | | | 700 | 5000 | 4700 | 4300 | 3700 | 3000 | 2520 | 1800 | 0 | | | | | |
| | | | | max 900 | 6900 | 6200 | 5760 | 5040 | 4200 | 3660 | 3200 | 1800 | 0 | | | | |
| VA MAJOR 60 | TF 230-400V 50 Hz | 2,5 | 1,87 | min 175 | 4320 | 3840 | 3000 | 0 | | | | | | | | | |
| | | | | 350 | 9000 | 7800 | 6000 | 3700 | 0 | | | | | | | | |
| | | | | 700 | 18000 | 15000 | 12000 | 8400 | 2500 | 0 | | | | | | | |
| | | | | max 900 | 22500 | 19560 | 15000 | 11220 | 3000 | 0 | | | | | | | |
| VA MAXI 80 | TF 230-400V 50 Hz | 5,5 | 4 | min 150 | 12000 | 10000 | 7500 | 0 | | | | | | | | | |
| | | | | 300 | 24600 | 22200 | 18900 | 12000 | 0 | | | | | | | | |
| | | | | 470 | 36000 | 34200 | 30000 | 24000 | 12000 | 0 | | | | | | | |
| | | | | max 600 | 43800 | 41400 | 36000 | 30000 | 16000 | 0 | | | | | | | |
| INV MINI 3/4" | MF 230V 50 Hz | TF 400V 50 Hz | 0,75 | 0,56 | min 180 | 150 | 0 | | | | | | | | | | |
| | | | | | 600 | 700 | 560 | 390 | 150 | 0 | | | | | | | |
| | 900 | 1000 | 900 | 840 | 720 | 540 | 450 | 350 | 0 | | | | | | | | |
| | max 1400 | 1620 | 1440 | 1320 | 1140 | 1020 | 900 | 800 | 600 | 400 | 0 | | | | | | |
| INV MIDEX 1"1/4 | MF 230V 50 Hz | TF 400V 50 Hz | 1 | 0,75 | min 180 | 600 | 480 | 0 | | | | | | | | | |
| | | | | | 600 | 2600 | 2300 | 2000 | 1400 | 800 | 400 | 0 | | | | | |
| | 900 | 3840 | 3480 | 3180 | 2760 | 2160 | 1800 | 1600 | 720 | 0 | | | | | | | |
| | max 1400 | 5760 | 5160 | 4800 | 4320 | 3600 | 3180 | 2800 | 1920 | 1200 | 0 | | | | | | |
| INV MINOR 40 | MF 230V 50 Hz | TF 400V 50 Hz | 2,5 | 1,87 | min 50 | 380 | 0 | | | | | | | | | | |
| | | | | | 175 | 1320 | 800 | 0 | | | | | | | | | |
| | 350 | 2750 | 2500 | 2100 | 1600 | 800 | 0 | | | | | | | | | | |
| | max 900 | 6900 | 6200 | 5760 | 5040 | 4200 | 3660 | 3200 | 1800 | 0 | | | | | | | |
| INV MAJOR 60 | MF 230V 50 Hz | TF 400V 50 Hz | 3 | 2,2 | min 50 | 1230 | 0 | | | | | | | | | | |
| | | | | | 175 | 4320 | 3840 | 3000 | 0 | | | | | | | | |
| | 350 | 9000 | 7800 | 6000 | 3700 | 0 | | | | | | | | | | | |
| | max 900 | 22500 | 19560 | 15000 | 11220 | 3000 | 0 | | | | | | | | | | |
| INV MAXI 80 | TF 230V 50 Hz | TF 400V 50 Hz | 5,5 | 4 | min 50 | 3800 | 0 | | | | | | | | | | |
| | | | | | 150 | 12000 | 10000 | 7500 | 0 | | | | | | | | |
| | 300 | 24600 | 22200 | 18900 | 12000 | 0 | | | | | | | | | | | |
| | max 600 | 43800 | 41400 | 36000 | 30000 | 16000 | 0 | | | | | | | | | | |
| INV MAXI Double 2Q | TF 230V 50 Hz | TF 400V 50 Hz | 7,5 | 5,5 | min 50 | 7600 | 0 | | | | | | | | | | |
| | | | | | 175 | 27000 | 24000 | 20000 | 13000 | 0 | | | | | | | |
| | 235 | 36000 | 33000 | 27500 | 20500 | 10000 | 0 | | | | | | | | | | |
| | max 470 | 72000 | 65000 | 56000 | 45000 | 30000 | 20000 | 0 | | | | | | | | | |
| INV MAXI Double 2H | TF 230V 50 Hz | TF 400V 50 Hz | 7,5 | 5,5 | min 50 | 3800 | 2000 | 0 | | | | | | | | | |
| | | | | | 175 | 14100 | 13500 | 12600 | 11400 | 9700 | 8600 | 7400 | 4500 | 0 | | | |
| | 235 | 19200 | 18500 | 17500 | 16200 | 14300 | 13200 | 12000 | 9000 | 5900 | 0 | | | | | | |
| | max 470 | 27600 | 26700 | 25500 | 24000 | 22200 | 21000 | 20000 | 17200 | 14800 | 9700 | 0 | | | | | |
| max 470 | 36000 | 35000 | 33600 | 32000 | 29700 | 28400 | 27000 | 23600 | 20600 | 14300 | 0 | | | | | | |

* MF = Monofase/Single-phase TF = Trifase/Three-phase